

FMM-7045 Multiplex Addressable Manual Stations

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Easy addressing with rotary switches
- ▶ Terminal connections and low current draw
- ▶ Key-lock reset
- ▶ Replaceable scored acrylic break rod option
- ▶ UL Listed and ADA compliant

The FMM-7045 Multiplex Manual Stations are UL Listed fire alarm initiating devices that can be connected along with other multiplex devices on the D7039 Multiplex Expansion Module. The FPD-7024 or D7024 Addressable Fire Alarm Control Panel (FACP) supervises the entire multiplex loop, including the FMM-7045 or FMM-7045-D manual stations, for troubles, alarms, and ground fault conditions. Because each manual station occupies only one address on the multiplex bus, it can be addressed for any point within the 9 to 255 range allowed by the multiplex expansion module.

These manual stations are generally installed near building exits such as stairways and doors, allowing persons evacuating the building to activate the fire alarm. They have optional scored acrylic breakrods and a pull handle that locks in the activated position, to allow easy identification of alarm activation points. These manual stations are high-quality units constructed entirely of non-toxic materials. They have a low profile and rounded edges to fit most design applications. All components are painted or have plated surfaces to inhibit corrosion. Non-corroding screw terminals are provided for wire connections.

They are manufactured in conformance with the standards set forth in the Americans with Disabilities Act (ADA).

Functions

Alarm Action

The single-action FMM-7045 has a white pull-down lever in its center. The dual-action FMM-7045-D has a white push lever above the white pull-down lever in its center. Pulling down the pull-down lever latches it into place and sends an alarm signal to the control panel over the multiplex bus. The pull-down lever cannot be reset unless the correct key is inserted into the manual station's lock and the unit is opened. The latching lever can then be restored to its normal position.

Certifications and approvals

Region	Certification	
USA	UL	UNIU: Boxes, Non-Coded (UL38)
	CSFM	see our website
	FDNY-CoA	#6173

Installation/configuration notes

Compatibility Information

The following table lists control panels compatible with the FMM-7045 and FMM-7045-D manual stations:

Control Panels
Active products:
FPD-7024
Legacy products:
D7024*
* with firmware revision 2.0 or greater and with a D7039 Multiplex Expansion module

Addressing

Addresses are set using three rotary switches. For programming information, refer to the *D7024 FACP Operation and Installation Guide* or the *FPD-7024 Operation and Installation Guide* and the *FMM-7045, FMM-7045-D Multiplex Addressable Manual Stations Installation Instructions*.

Mounting

The manual stations are for indoor use only.

Notice

If a pull station is needed for outdoor use or in an unheated area, use an FMM-100 Family Pull Station rated for the environment and wired to a multiplex module within the interior of the building.

The FMM-7045 manual stations flush or surface mount on a standard four-inch square back box with a single-gang mud ring so that the total depth of the box is at least 2.25 in. (5.7 cm).

Notice

These manual stations do **not** fit an FMM-100BB-R Back Box.

Wiring

The terminal block accepts wiring up to 12 AWG (ISO 4 mm²) in diameter.

For multiplex wiring information, refer to the *D7039 Installation Instructions*.

Parts included

Quant.	Component
1	Manual station
1	FMM-100GR Scored Acrylic Breakrod
1	D102 Key (1358)
1	Literature pack

Technical specifications

Environmental Considerations

Environment:	Dry, indoor
Radio Frequency Interference (RFI) Immunity:	No alarm on critical frequencies in the range from 26 MHz to 950 MHz at field strengths less than 30 V/m.
Temperature (Operating):	+32°F to +120°F (0°C to +49°C)

Mechanical Properties

Dimensions (H x W x D):	4.75 in. x 3.75 in. x 3.25 in. (12 cm x 9.5 cm x 8.2 cm)
Material:	Die cast zinc alloy and steel

Power Requirements

Current Draw (Mux Bus Average):	Alarm: 0.55 mA Standby: 0.55 mA
Voltage (Operating):	12 VDC nominal (provided by the MUX bus)

Ordering information

FMM-7045 Single-Action Manual Station

The single-action manual station is UL listed and meets Americans with Disabilities Act (ADA) requirements. Its address on the polling circuit is easily set with rotary switches. The pull handle locks in the activated position and is reset by opening the unit with a key and then relocking it.

Order number **FMM-7045**

FMM-7045-D Double-Action Manual Station

The double-action manual station is UL listed and meets Americans with Disabilities Act (ADA) requirements. Its address on the polling circuit is easily set with rotary switches. The pull handle locks in the activated position and is reset by opening the unit with a key and then relocking it.

Order number **FMM-7045-D**

Accessories

D102 Replacement Key

Replacement key (#1358) for LOCK-1358 and the D101 lock.

Order number **D102**

FMM-100GR Scored Acrylic Break Rods

Scored acrylic rods (12 per package)

Order number **FMM-100GR**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com