

# FMM-100 Die-cast Metal Fire Alarm Manual Stations

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Single or dual action
- ▶ Terminal connections
- ▶ Gold-plated alarm contacts for corrosion resistance
- ▶ Surface or weatherproof back boxes

The FMM-100 family are versatile, high-quality, metal fire alarm manual stations. Single-action or dual-action models are available. All models come with a key lock and contain gold-plated contacts to resist corrosion.

## Functions

### Operation Single-action

When the bar on the front of the manual station is pulled, it latches open and is easily visible from 50 ft (15 m). Reset the activation bar by opening the manual station with the key and placing the activation bar in its normal upright position. An optional scored acrylic break rod is available.

### Dual-action

With the dual-action configuration the upper bar on the front of the manual station rotates inward allowing the activation bar to be grasped and operated by a single hand.

## Certifications and approvals

| Region | Certification |   |
|--------|---------------|---|
| USA    | UL            | UNIU: Boxes, Non-Coded (UL38),<br>UNIU7: Boxes, Non-Coded Certified for<br>Canada (cULus) |
|        | CSFM          | see our website   |
|        | NYC-<br>MEA   | 382-94-E, Vol. VI   |

## Installation/configuration notes

### Compatibility Information

These manual stations are compatible with all Bosch Security Systems, Inc. Fire Alarm Control Panels.

### Mounting Considerations

These manual stations can be surface mounted on either the FMM-100BB-R Surface-mount Back Box or the FMM-100WPBB-R Weatherproof Back Box. They can also be flush mounted on a standard single-gang back box.

**Notice**

When properly mounted on the FMM-100WPBB-R Weatherproof Back Box, these manual stations meet UL requirements for outdoor use.

To comply with ADA standards, the manual station must be less than 48 in. (1.2 m) above the floor for front wheelchair access and less than 54 in. (1.3 m) above the floor for side wheelchair access.

**Parts included**

| Quant. | Component                   |
|--------|-----------------------------|
| 1      | Manual station              |
| 1      | D102 Key (1358 key)         |
| 1      | FMM-100GR Acrylic Break Rod |
| 1      | Hardware pack               |
| 1      | Literature pack             |

**Technical specifications****Environmental**

|                          |                                  |
|--------------------------|----------------------------------|
| Relative Humidity:       | 90% at +100°F (+38°C)            |
| Temperature (operating): | -40°F to +150°F (-40°C to +66°C) |

**Mechanical**

|                         |  |
|-------------------------|--|
| Color:                  | Red  |
| Dimensions (H x W x D): | 4.75 in. x 3.25 in. x 1.1 in.<br>(12 cm x 8.3 cm x 2.8 cm) |
| Material:               | die-cast metal   |

**Inputs**

|                |                          |
|----------------|--------------------------|
| Switch Rating: | 1 A at 30 VDC or 125 VAC |
|----------------|--------------------------|

**Ordering information****FMM-100SATK Single-action Manual Station (red)**

Versatile, high-quality, metal single-action fire alarm manual station with key lock and gold-plated contacts  
Order number **FMM-100SATK**

**FMM-100SATK-NYC Single-action Manual Station for New York City**

Versatile, high-quality, metal single-action fire alarm manual station for New York City with key lock and gold-plated contacts  
Order number **FMM-100SATK-NYC**

**FMM-100DATK Dual-action Manual Station (red)**

Versatile, high-quality, metal dual-action fire alarm manual station with key lock and gold-plated contacts  
Order number **FMM-100DATK**

**Accessories****D102 Replacement Key**

Replacement key (#1358) for LOCK-1358 and the D101 lock.

Order number **D102**

**FMM-100BB-R Surface-mount Back Box (red)**

Red cast-metal back box

Order number **FMM-100BB-R**

**FMM-100WPBB-R Weatherproof Back Box (red)**

Red cast-metal weatherproof back box

Order number **FMM-100WPBB-R**

**FMM-100GR Scored Acrylic Break Rods**

Scored acrylic rods (12 per package)

Order number **FMM-100GR**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com